

SG4-R-*

OPTICAL RECEIVER NODE SERIES



FEATURES

- Enables bandwidth expansion via downstream node segmentation
- Supports CWDM, DWDM and CORWave® multiwavelength technologies
- Maximizes network flexibility with wide input range
- Reduces the need for costly optical amplifiers
- Easy Plug and Play installation and operation to minimize service time



PRODUCT OVERVIEW

ARRIS SG4000 standard and high gain receivers use an integrated optical hybrid photo detector and Gallium Arsenide (GaAs) technology to improve RF performance over the entire 1 GHz passband. The high gain receiver provides a lower optical input range, enabling the receiver to overcome multiwavelength passive loss while maintaining typical RF output levels. Temperature compensation circuitry automatically responds to the receiver's gain and requires no set-up procedure.

The SG4-R-* receivers feature a built-in microprocessor for monitoring the optical power, module current, and module enable status. An optical power DC voltage test point, along with a wave-length selection jumper facilitates accurate measurements of input power. A -20 dB test point enables you to measure carriers throughout the forward band, and gain adjustments are made with a JXP style interstage pad. Output slope is generated by the Linear Midstage Equalizer (LME) plug-in that is can be changed by removing the receiver cover. Module status indicators help reduce troubleshooting time, and the SG4-R-* can be hot-swapped in the field, providing true plug and play functionality.

SPECIFICATIONS

Parameter	Standard Gain	High Gain	
	SG4-R-100/SC	SG4-R-H-100/SC	
Optical Performance			
Optical Input Return Loss	40 dB minimum	40 dB minimum	
Absolute Maximum Optical Input Power	+ 3 dB maximum	+3 dB maximum	
Recommended Optical Input Power Range	-3 dBm to + 2.0 dBm	-6 dBm to + 2.0 dBm	
Optical Power Test Point Scale Factor	1.0 ± 0.20 V/mW	1.0 ± 0.20 V/mW	
RF Performance			
RF Passband	54 MHz to 1003 MHz	54 MHz to 1003 MHz	
Gain at 1003 MHz @ -3 dBm Input	46.5 dB minimum	50.5 dB minimum	
Flatness	1.3 dB P-V maximum	1.3 dB P-V maximum	
Slope (w/LME-100-8 Installed)	9 ± 1 dB	9 ± 1 dB	
RF Return Loss (52 to 900 MHz)	16 dB minimum	16 dB minimum	
Test Point Flatness	1 dB P-V maximum	1 dB P-V maximum	
Equivalent Input Noise Current	8 pA/Hz ^{1/2} maximum	5.5 pA/Hz ^{1/2} maximum	
DC Performance			
DC Supply Current (24 Volts)	525 mA maximum	525 mA maximum	
DC Supply Current (5 Volts)	50 mA maximum	50 mA maximum	
Distortion			
Composite Triple Beat (CTB)	-71 dBc minimum ¹	-72 dBc minimum ²	-73 dBc minimum ³
Composite Second Order (CSO)	-65 dBc minimum ¹	-67 dBc minimum ²	-72 dBc minimum ³
Carrier to Noise Ratio (CNR)	50.5 dB minimum ¹	48 dB minimum ²	51 dBc minimum ³
Digital Distortion			
Modulation Error Rate (MER)	Not specified	39	
Bit Error Rate (BER)*	Not specified	1x10 ⁻⁹	
Carrier to Composite Noise (CCN)	Not specified	42	
Optical Input Alarm Range			
High (HIHI)	1.6 mW (2 dBm)	1.6 mW (2 dBm)	
Low (LOLO)	0.4 mW (-4 dBm)	0.2 mW (-7 dBm)	

Notes:

- Using GX2-LM1000B9, 20km optical link, -3 dBm optical input power, nominal wavelength of 1310 nm, and a LME 1-8. 79 channels CW plus noise to 1 GHz (-6 dB down from Analog) with a +40 dBmV maximum output level at 550 MHz.
- 79 analog NTSC channels 55.25 to 547.25 MHz, 75 digital NTSC channels 552 to 1002 MHz, using LM1000E9 transmitter (3.6% OMI per analog channel), 20 km, -6 dBm at receiver +44 dBmV output at 547.25 MHz.
- 79 analog NTSC channels 55.25 to 547.25 MHz, 75 digital NTSC channels 552 to 1002 MHz, using LM1000E9 transmitter (3.6% OMI per analog channel), 20 km, -3 dBm at receiver +44 dBmV output at 547.25 MHz.

RELATED PRODUCTS

CHP Transmitters	Optical Patch Cords
SG4000 Modular Node	Optical Passives
Fiber Service Cable	Installation Services

Note: Specifications are subject to change without notice.

Copyright Statement: ©ARRIS Enterprises, Inc. 2015 All rights reserved. No part of this publication may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from ARRIS Enterprises, Inc. ("ARRIS"). ARRIS reserves the right to revise this publication and to make changes in content from time to time without obligation on the part of ARRIS to provide notification of such revision or change. ARRIS and the ARRIS logo are all registered trademarks of ARRIS Enterprises, Inc. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and the names of their products. ARRIS disclaims proprietary interest in the marks and names of others. The capabilities, system requirements and/or compatibility with third-party products described herein are subject to change without notice.

SG4000 Optical Receiver Node_DS_21NOV14