

# MAXNET®

## RF & L-Band Signal Management

Patented  
U.S.# 6,842,348



### Active Products

### Power Supply:

#### 24V Power Supply Specifications (for use with RF & L-Band)

ELECTRICAL SPECIFICATIONS	REMOTE POWER SUPPLIES MNRPS or MNRPSCM (1)	AC POWER SUPPLIES MNAC-110 or MNAC-110CM(1)	AC POWER SUPPLIES MNAC-220 or MNAC-220CM(1)	DC POWER SUPPLIES MNDC or MNDCCM(1)
<b>INPUT</b>				
INPUT VOLTAGE	24.0 ± 0.5 VDC	110 ± 10 VAC	220 ± 20 VAC	48.0 ± 12.0 VDC
FREQ	DC	50/60 Hz	50/60 Hz	DC
INPUT CURRENT	(3)	2.0 Amps AC	1.0 Amps AC	2.5 Amps DC (48 Vdc)
POWER FACTOR	NA	>0.8	>0.8	NA
<b>OUTPUT</b>				
OUTPUT VOLTAGE	23.5 ± 0.5 VDC	24.0 ± 1.0 VDC	24.0 ± 1.0 VDC	24.0 ± 1.0 VDC
DC OUTPUT CURRENT	3.6 Amps (max.) (3,4)	3.6 Amps (max.) (5)	3.6 Amps (max.) (5)	3.6 Amps (max.) (5)
RIPPLE VOLTAGE	NA	200 mV P-P (max.)	200 mV P-P (max.)	200 mV P-P (max.)
MAXIMUM POWER OUTPUT	N/A	86.4 Watts	86.4 Watts	86.4 Watts
<b>OTHER</b>				
EFFICIENCY	>95%	>80%	>80%	>80%
OPERATING TEMPERATURE	-40°C to +60°C	-40°C to +60°C	-40°C to +60°C	-40°C to +60°C
APPROVALS	N/A	Power Supply Component: UL, CSA, CE; Entire Module: cULus, FCC	Power Supply Component: UL, CSA, CE; Entire Module: cULus	Power Supply Component: UL, CSA, CE; Entire Module: cULus, FCC
TEST POINT	Front Panel (Red(+), Blk(Com))	Front Panel (Red(+), Blk(Com))	Front Panel (Red(+), Blk(Com))	Front Panel (Red(+), Blk(Com))
24V POWER INDICATOR	Front Panel LED	Front Panel LED	Front Panel LED	Front Panel LED
24V FAILURE NOTIFICATION (2)	Form 'A' Relay (MNRPS) Form 'A' Relay (MNRPSCM)	Form 'C' Relay (MNAC-110) Form 'A' Relay (MNAC-110CM)	Form 'C' Relay (MNAC-220) Form 'A' Relay (MNAC-220CM)	Form 'C' Relay (MNDC) Form 'A' Relay (MNDCCM)
CURRENT VARIATION NOTIFICATION (1)	Rear Panel Form 'A' Relay and Front LED (MNRPSCM only)	Rear Panel Form 'A' Relay and Front LED (MNAC-110CM only)	Rear Panel Form 'A' Relay and Front LED (MNAC-220CM only)	Rear Panel Form 'A' Relay and Front LED (MNDCCM only)
TERMINAL BLOCK WIRING	# 14 AWG	# 14 AWG	# 14 AWG	# 14 AWG
WEIGHT	1.5 lbs / 700 g	2.9 lbs / 1300 g	2.9 lbs / 1300 g	2.2 lbs / 980 g

**NOTES:**

1. CM on the end of the part number indicates current monitoring capabilities. Current through the chassis interface is monitored. Fluctuation in DC current greater or less than 200mA from nominal operating level is annunciated by opening a contact wired to the rear terminal block and turning 'off' the current monitor LED.
2. 24V failure notification is initiated when DC voltage level drops to less than 22 VDC.
3. 24V A and 24V B inputs are diode 'OR'd' prior to connection to the chassis power bus interface connector. Maximum DC current to the chassis is 3.6 Amps.
4. Maximum DC current delivered through the remote power supply interface connector (to chassis power bus).
5. Total DC output current delivered through the power supply interface connector (to chassis power bus) and through the output terminals on the rear of the power supply.

#### Rear Panel Terminal Block Assignment Specifications

TB #	REMOTE POWER SUPPLY MNRPS	REMOTE POWER SUPPLY WITH CURRENT MONITOR MNRPSCM	AC POWER SUPPLIES MNAC-110 and MNAC-220	AC POWER SUPPLIES WITH CURRENT MONITOR MNAC-110CM and MNAC-220CM	DC POWER SUPPLY MNDC	DC POWER SUPPLY WITH CURRENT MONITOR MNDCCM
1	P24V IN A	P24V IN A	P24V OUT (1)	P24V OUT (1)	P24V OUT (1)	P24V OUT (1)
2	COM A	COM A	COM/GND	COM/GND	COM/GND	COM/GND
3	P24V IN B	P24V IN B			P48V IN	P48V IN
4	COM B	COM B			N48V IN	N48V IN
5	RLY NO (V)	RLY NO (V)	RLY NO	RLY NO (V)	RLY NO	RLY NO (V)
6	RLY COM	RLY COM	RLY COM	RLY COM	RLY COM	RLY COM
7	RLY NO (I)* (* - used for MNRPSCM only)	RLY NO (I)* (* - used for MNRPSCM only)	RLY NC	RLY NO (I)	RLY NC	RLY NO (I)

**NOTES:**

1. 24V Output on rear panel terminal block allows for daisy-chain powering to other active MAXNET chassis which utilize MAXNET remote power supplies.



## RF & L-Band Signal Management

### Power Supply (cont'd):

#### Ordering Information

Part Number	Description
MNRPS	24V, 3.6A Remote Powering Unit
MNRPSCM	24V, 3.6A Remote Powering Unit with Current Monitoring
MNAC-110	110VAC to 24V, 3.6A Diode or'd Redundant Power Supply
MNAC-110CM	110VAC to 24V, 3.6A Power Supply with Current Monitor
MNAC-220	220VAC to 24V, 3.6A Diode or'd Available (Consult PCI Factory)
MNAC-220CM	220VAC to 24V DC, 3.6A Power Supply with Current Monitor
MNDC	-48VDC to 24V, 3.6A True Load Sharing Redundant Power Supply
MNDCCM	-48VDC to 24V, 3.6A Power Supply with Current Monitor